

This Page Is Inserted by IFW Operations
and is not a part of the Official Record

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images may include (but are not limited to):

- BLACK BORDERS
- TEXT CUT OFF AT TOP, BOTTOM OR SIDES
- FADED TEXT
- ILLEGIBLE TEXT
- SKEWED/SLANTED IMAGES
- COLORED PHOTOS
- BLACK OR VERY BLACK AND WHITE DARK PHOTOS
- GRAY SCALE DOCUMENTS

IMAGES ARE BEST AVAILABLE COPY.

**As rescanning documents *will not* correct images,
please do not report the images to the
Image Problem Mailbox.**

VARIABLE AMPLITUDE REGULATOR

RELATED APPLICATION:

This application is a continuation-in-part of co-pending application Serial No. 10/199,646 filed on July 7, 2002.

BACKGROUND

Power Factor Correction (PFC) circuits are used to minimize unwanted disturbances in AC power lines, and to provide a constant DC output voltage under all load conditions. The AC line disturbances are caused by normal operation of DC powered electrical equipment, and are exhibited as phase shift of the AC input current and distortion of the current waveform. The PFC minimizes the distortion and corrects the phase shift. Existing PFC control circuits are complex, difficult and time consuming to implement, and have a limited dynamic range. By incorporating a power factor correction circuit between the alternating current supply and the direct current supply connected to the load, however, harmonic distortion in the AC power line is reduced; and the operational characteristics of some electrical equipment is improved. It is desirable to provide an improved PFC control circuit which is simple, has a wide dynamic range and requires minimal expertise to implement using a variable Amplitude Regulator (VAR) to accomplish this by using simple resistive scaling, instead of complex multiply and divide circuit functions, to produce the PFC control signal.

SUMMARY OF THE INVENTION

It is an object of this invention to provide an improved power factor correction (PFC) system.

It is another object of this invention to provide an improved variable amplitude regulator (VAR) signal interface in a switch-mode PFC system.

1 It is an additional object of this invention to provide an improved analog variable amplitude
2 voltage regulator for use in a power factor correction system.

3 It is a further object of this invention to provide an improved variable amplitude voltage
4 regulator (VAR) for use in a power factor correction system in which the VAR interface functions
5 as a resistor scaling network utilizing at least one variable resistor for responding to a wide dynamic
6 range of load variations.
7

8 In accordance with a preferred embodiment of the invention, a variable amplitude voltage
9 regulator (VAR) utilized in a power factor correction system operates as a resistor scaling network.
10 The network consists of at least one variable resistor. A source of rectified alternating current
11 input voltage (ACR) is coupled to the resistor scaling network. The output of a voltage error
12 differential amplifier (VES) is coupled through a filter to a digital signal processor (DSP) which
13 converts the VES voltage into a proportional duty ratio (DR) signal. The signal then controls the
14 resistance value of the variable resistor such that the scaling network produces a demand level
15 control signal (DLS) for the power factor correction circuit.
16
17

18 BRIEF DESCRIPTION OF THE DRAWING:
19

20 Figure 1 is a schematic diagram of a power factor correction circuit incorporating a preferred
21 embodiment of the invention;

22 Figure 2 illustrates waveforms useful in understanding the operation of the system shown in
23 Figure 1;

24 Figure 3 is a simplified schematic diagram of a resistor scaling network useful in explaining
25 the operation of the preferred embodiments of the invention; and
26

1 Figure 4 is a detailed schematic diagram of an embodiment of the invention; and

2 Figure 5 is a detailed schematic diagram of another embodiment of the invention.

3 DETAILED DESCRIPTION

4
5 Reference now should be made to the drawings, in which the same reference numbers are
6 used throughout the different figures to designate the same or similar components. Figure 1 is a
7 schematic diagram of a switch-mode boost converter of a typical configuration, which is used for
8 a power factor correction circuit. In the circuit of Figure 1, the location and functional
9 interconnections of a variable amplitude regulator interface (VAR) are illustrated.

10 In the circuit shown in Figure 1, standard alternating current (AC) utility power is connected
11 across the input terminals 10, also designated as ACL-NTL. Although a specific implementation
12 of a switch-mode boost converter is illustrated in Figure 1, other implementations may be used. The
13 alternating current input voltage is filtered by a common mode choke consisting of a pair of
14 independent windings 14, 16 and a pair of capacitors 18 and 20 interconnected in a conventional
15 manner across the AC input line 10. This filtered alternating current voltage is applied to a full wave
16 bridge rectifier 22. The rectifier 22 output is connected to a switch-mode boost stage consisting of
17 an inductor 28, a capacitor 29, a transistor (MOSFET) 24 and a resistor 26. The capacitor 29 is
18 connected across the DC terminals of the rectifier 22; and the positive terminal of the rectifier 22 is
19 connected through the inductor 28 and an additional diode 25 to the positive DC output load terminal
20 27. The negative or return terminal of the rectifier 22 is coupled to the lower side of the resistor 26,
21 shown in Figure 1. A large electrolytic capacitor 50 is placed across the DC output terminals to
22 smooth the output voltage and current.

23
24
25 In order to achieve the desired sinusoidal current flow in the AC power line (see Figure 2,
26

1 top set of waveforms), it is necessary to regulate the current flow through the power inductor 28 in
2 the switch-mode boost stage. At any instant in time, the magnitude of the current in the inductor 28
3 is equal to the absolute value of the alternating line current. This is indicated by the designation I_{ac}
4 in Figure 1. As is apparent from Figure 1, this same current flows through the transistor 24 and the
5 resistor 26, which are connected in series with the inductor 28 across the terminals of the rectifier
6 22. Regulation of this current through the inductor 28 and the resistor 26 is controlled by a pulse
7 width modulation circuit (PWM) 30, used to adjust the on/off duty ratio of the MOSFET transistor
8 24.
9

10 The functional characteristics of pulse width modulation circuits, such as the circuit 30, are
11 well understood and a detailed description of the operation of such a circuit is not considered
12 necessary here. The PWM circuit 30 shown in Figure 1 uses an average current-mode control
13 method to regulate the current through the inductor 28, as a function of the I_{ac} feedback current from
14 the resistor 26 and of a demand level signal (DLS) 32 provided by a PFC control circuit. The output
15 of the PWM circuit 30 connects through a driver 34 to the gate of the MOS FET 24 to modulate its
16 on/off duty ratio in order to control current flow through the inductor.
17

18 Required inputs to the PFC control circuit are the AC rectified voltage signal (ACR) and the
19 voltage error signal (VES). The ACR is generated through the resistor divider 36 and 38, and the
20 VES is the output of the differential amplifier 44 on the lead 45. The PFC circuit causes the current
21 waveform in the power inductor 28 to be congruent and in phase with the AC voltage waveform.
22 It also responds to changes in load by adjusting the amplitude of the AC input current. In this new
23 PFC circuit implementation which is illustrated in Figure 1, the control functions needed for power
24 factor corrections are provided by the VAR interface.
25
26

1 The VAR interface causes the waveform of the current in the power inductor 28 to be
2 congruent and in phase with the rectified AC input voltage (ACR), as indicated in Figure 2. At the
3 same time, the Iac RMS value must be regulated to maintain the DC output voltage for various
4 changing load conditions. Load variations are detected by a voltage error differential amplifier 44,
5 which produces a voltage error signal VES on the line 45. This signal is produced by comparing the
6 output DC voltage on the load terminal 27, as it appears across a resistor divider consisting of the
7 resistor 46 and the resistor 48 coupled to one input of the amplifier 44 against a fixed reference
8 provided across the Zener diode 52 connected to the other input of the amplifier 44. The filter
9 capacitor 50 also is connected across the DC output, as is readily apparent from Figure 1.

10
11 Whenever changes occur in the direct current load connected across the positive direct
12 current terminal 27 and the negative or return (RTN) terminal shown in Figure 1, a corresponding
13 change or variation occurs in the output of the amplifier 44 in the VES signal applied over the line
14 45. The VES control signal on the line 45 is supplied as one of two inputs to the variable amplitude
15 regulator interface circuit (VAR) 42. The other input is the rectified AC voltage (ACR) obtained
16 from a voltage divider consisting of the resistors 36 and 38 connected across the output terminals
17 of the rectifier 22. The two signals are combined to produce the control signal DLS for operating
18 the pulse width modulator 30, which in turn controls the conductivity of the FET transistor 24 for
19 regulating the current flow through the power inductor 28, as described above.

20
21 As mentioned previously, in a power factor correction (PFC) application, it is desirable to
22 change the RMS value of the current, but not the wave shape, to prevent harmonic distortion of the
23 alternating input current applied at the terminal 10. Consequently, whenever the load connected to
24 the terminal 27 changes, the system must both regulate the wave shape of the incoming alternating
25

current signal on the terminals 10, as well as the changes in the DC load current, without much delay. By employing the VAR interface 42, which can respond to both slow changes of the DC load as well as stepped changes or rapid changes, the switch-mode modulator 30, which controls the operation of the transistor 24, is allowed to run at frequencies as low as 25 Khz, in contrast to systems of the prior art which typically had a 80 Khz lower limit.

The VAR interface produces a single output, the demand level signal (DLS), which is used as a control input by the PWM in the power stage of the PFC. This single output serves two functions; correction of the AC current waveform and phase, and adjustment of the AC current amplitude in response to changes in load.

There are two inputs to the VAR interface, the AC rectified voltage (ACR), and the voltage error signal (VES). The ACR is the output of the bridge rectifier 22 through the resistor divider 36 and 38, and is used to control the waveform and phase of the AC input current. The VES is the output of the differential amplifier 44, and is used to control the average value of the AC input current.

The VAR interface design is based on a simple concept using a variable resistor ratio to control the amplitude of the signal (acrx) derived from the rectified AC input voltage (ACR). This control arrangement is illustrated in a simplified circuit diagram shown in Figure 3. The relationship between the ACR and the DLS is defined by the following equation:

$$DLS = \left(\frac{R2}{R1 + R2} \right) \times \left(1 + \frac{R4}{R3} \right) \times ACR$$

In a typical application, the VES is connected to the terminal 45 to control the variable resistor 64. A resistor 80 and a capacitor 82 form a low pass filter to block AC line frequency

1 ripple, from causing harmonic distortion. A resistor divider consisting of a resistor 62 (R1) and a
2 variable resistor 64 (R2) produce a reduced ACR voltage which is connected to the (+) input of a
3 differential amplifier 68. The amplifier 68 is used as an impedance buffer and a fixed gain stage as
4 determined by the values of resistors 70 (R3) and 72 (R4). The output of the amplifier 68 connects
5 to the terminal 32, the demand level signal (DLS). Based on the circuit configuration shown in
6 Figure 3, it is obvious that a change in the resistance of variable resistor 64 (R2) produces a
7 proportional change in the demand level signal (DLS). The voltage error signal 45 (VES) controls
8 the value of the variable resistor 64 (R2), which in turn controls the input of the amplifier 68. The
9 output of the amplifier 68 is the demand level signal (DLS) on terminal or line 32. The circuit of
10 Figure 3 also includes a feedback resistor 72 and a filter capacitor 74, interconnected in a
11 conventional manner.
12

13 In the simplified circuit of Figure 3, it is apparent that the VAR interface which is illustrated
14 produces a demand level signal (DLS) on the line 32, which satisfies both of the desired control
15 functions of regulating the RMS value and maintaining the sinusoidal waveform in the current of
16 the inductor 28. This is accomplished by combining the two input signals ACR and VES on the
17 terminals 40 and 45, respectively. Because the value of the resistor 64 may be varied, the value of
18 the DLS output on the line 32 is variable. By dynamically controlling the resistivity of the resistor
19 R2, the variation in the DLS signal on the line 32 effectively may be utilized to control the PWM
20 30 of Figure 1 to maintain the output voltage steady as the load changes, and to keep the input
21 current in phase and congruent with the AC line voltage applied across the terminals 10.
22

23 Reference now should be made to Figure 4, which is a detailed schematic diagram of the
24 VAR circuit 42 of a preferred embodiment of the invention. The circuit of Figure 4 is the specific
25
26

1 implementation of an actual configuration of the resistor scaling network described generally in
2 conjunction with Figure 3.

3 In the circuit of Figure 4, the ACR signal is applied on the terminal 40; and the VES signal
4 is applied on the lead 45, as in the case of the circuit of Figure 3. The input return signal is shown
5 at the bottom of Figure 4 as RTN. The output differential amplifier 68 is illustrated providing the
6 DLS output on the line 32, and is shown with the feedback resistor 72 connected in series with the
7 resistor 70 to provide gain to the differential amplifier 68. The input obtained from the scaling
8 circuit is supplied to the + terminal of the amplifier 68.

9 As shown in Figure 4, the ACR signal on terminal 40 connects through the resistor 62 to the
10 drains of three identical JFETs 92, 94, and 96. These JFET devices are connected in parallel with
11 each other and function as a voltage controlled variable resistance. Many different field effect
12 transistor (FET) types are available and can be used; however, the VAR circuit schematic illustrated
13 in Figure 4 is designed to incorporate a type J175. The voltage error signal (VES) applied at
14 terminal 45 provides the control for regulating the resistance of the three JFETs, 92, 94 and 96. The
15 frequency response of the VAR interface is tailored to accommodate three basic requirements: low
16 harmonic distortion, fast reaction to sudden changes in AC input voltage, and fast reaction to sudden
17 changes in DC output (load) current.

18 In order to achieve low harmonic distortion and a power factor of 0.99 or better, it is
19 necessary to insert a low pass filter between the VES terminal 45 and the gates of the three JFET
20 devices 92, 94 and 96. This filter is necessary to block the AC line frequency ripple, which is
21 superimposed on the voltage error signal (VES). The AC line frequency ripple occurs in PFC
22 circuits because the AC input current is cyclical and the DC current is nearly constant during steady
23
24
25
26

1 state operation. In this implementation, the filter consists of a network of seven components, namely
2 resistors 78, 80 and 86; capacitors 82 and 88; and diodes 84 and 85. The selection of each
3 component is based on specific functional requirements. Resistors 78 and 86, and capacitor 88 are
4 chosen to form a high frequency attenuator which reduces switching noise in the VAR interface.
5 Resistor 80 and capacitor 82 form a low pass filter to block the AC line frequency ripple to achieve
6 low harmonic distortion.

7 The gates of the transistors 92, 94 and 96 are connected in common to a filter network which
8 includes resistors 78 and 86 and a capacitor 88 connected between the VES input terminal 45 and
9 RTN. A resistor 80, having a high value of resistance (typically on the order of 100 k Ohm), in
10 conjunction with a capacitor 82, operates as an input filter having an RC time constant which
11 preferably is 100 ms or longer than the time constant provided by the filter including the resistor 86
12 and the capacitor 88. This time constant assures a very constant gate control voltage on the gates
13 of the JFETS 92, 94 and 96 for steady state or slow variations of the control signal VES on the
14 terminal 45.
15

16 To provide a faster response during step load or rapid load changes, a pair of opposite
17 conductivity diodes 84 and 85 are connected in parallel to bypass the resistor 80. The forward
18 voltage drop of these diodes is approximately 0.6 Volts; so that VES level changes on the terminal
19 45 of 0.6 Volts or greater are propagated through the resistor 78 and the diodes 84 and 85 to the
20 gates of JFETs 92, 94 and 96, with a time constant of 2 ms or less, since the resistor 80 essentially
21 is out of the circuit for such greater magnitude step load changes. Small perturbations (less than +/-
22 0.5 V) are attenuated by the large value of resistor 80 and capacitor 82. The acrx signal is connected
23 to the (+) input of amplifier 68. This amplifier is configured as a voltage follower with gain, and
24
25
26

provides the demand level signal 32 (DLS), which is a low impedance output. The amplifier gain is set by the values of the resistors 70 and 72, which can be selected to meet specific DLS output requirements.

By providing the two different time constants through the filter circuit at the gates of the transistors 92, 94 and 96 with different RC combinations, the system is allowed to accommodate a slow response for steady state and slow variations in the DC load, as well as a fast response for step load changes using the VAR interface circuit. It is important to note that the DLS output on the terminal 32 is congruent with the rectified AC line voltage (ACR) and that there is very little phase shift between the signals, as illustrated in the idealized waveforms of Figure 2. These characteristics are significant because the DLS output is the control reference for the PWM 30, which in turn regulates the AC line input current by controlling the on/off duty ratio of the transistor 24, as described previously in conjunction with Figure 1.

Phase shift and waveform irregularities contribute to harmonic distortion and reduced power factor, as is well known. By utilizing the dynamic control response of the circuit of Figure 4, a simple and accurate analog control circuit is provided for utilization in a power factor correction application.

Figure 5 illustrates another variation of the system employing a bi-polar transistor and a digital signal processing (DSP) circuit in place of the JFET devices 92, 94 and 96 of Figure 4 to perform the variable resistor function. The use of bi-polar transistors permits the implementation of a single adjustable duty ratio (DR) signal capable of controlling a single phase input or a two-phase or three-phase system. The control transistor is connected in parallel with a relatively large resistor and the transistor is switched on and off in varying amounts (varying duty cycle) to control

1 the average resistance of the variable resistor consisting of the parallel-connected transistor and
2 resistor. This implementation is effective for single-phase or multiple phase (such as three-phase)
3 operation.

4 In Figure 5, the ACR input 40 and the VES input 45 to the VAR circuit represented in Figure
5 5 are the same as shown in Figure 4. The same low pass filter circuit of Figure 4, connected between
6 the VES terminal 45 and the gates of the JFET devices also is employed in Figure 5 between the
7 VES terminal 45 and the input to a digital signal processor (DSP) circuit 102. This processor circuit
8 essentially comprises a saw tooth generator and a comparator to provide a pulse width modulation
9 of squarewave output pulses on the output terminal thereof. These output pulses are supplied
10 through a coupling resistor 110 to the base of a bi-polar NPN transistor 112. A typical circuit which
11 may be used for the DSP circuit 102 is a UNITRODE No. UCC3889. Other commercially available
12 DSP circuits, however, could be used as well as the UNITRODE circuit to provide the same pulse
13 width modulated output.
14

15 The output applied through the coupling resistor 110 to the transistor 112 has a proportional
16 duty ration (DR) at a fixed frequency above the audible range. A filter comprising a resistor 104 and
17 capacitor 106 is coupled between the VCC input to the DSP circuit 104 and the RC/CT input
18 terminal. Another coupling resistor 108 connects the output of the low pass filter to the comparator
19 input of the DSP circuit. The operation of the DSP circuit essentially converts the analog VES input
20 at the output of the low pass filter into a digital signal with a varying duty cycle. This signal is used
21 to switch on and off the transistor 112, the collector emitter path of which is connected in parallel
22 with a relatively high value resistor 98 between the DLS output terminal 32 and the RTN line.
23
24

25 The output of the variable resistor comprising the transistor 112 and the fixed high value
26

1 resistor 98 is filtered by another low pass filter comprising the resistor 114, capacitor 116, and
2 resistor 66. This filter is used since there is a short delay between the DLS and ACR signals as a
3 result of their low pass filter coupled to the VES terminal 45 required to attenuate the modulation
4 switching frequency. Since the ACR and DLS signals are line frequency related (50/60 Hz), it is
5 reasonable to use an RC averaging filter for a 62 KHz modulated signal.

6 For the circuit design and component selection of the circuit shown in Figure 5, DLS (the
7 signal appearing on terminal 32) is defined by the following equation:

8
$$DLS = [(R112)/(R112 + R98)] \times (1-DR) \times ACR$$

9 The foregoing description of the preferred embodiment of the invention is to be considered
10 as illustrative and not limiting. Various changes and modifications will occur to those skilled in the
11 art for performing substantially the same function, in substantially the same way, to achieve
12 substantially the same result, without departing from the true scope of the invention as defined in
13 the appended claims.
14
15
16
17
18
19
20
21
22
23
24
25
26